


Problem 20

The system is composed of a linear system to be stabilized, a non-linear actuator and some fast stable unmodeled dynamics of the actuator. The general detailed problem description is singled out.



1. The system to be stabilized: $\dot{w} = Aw + Bv$, $w \in \mathbb{R}^3, v \in \mathbb{R}$ is the input,

$$A = \begin{pmatrix} 1 & -1 & 1 \\ 1 & -1 & 0 \\ 1 & 0 & 1 \end{pmatrix}, \quad B = \begin{pmatrix} 1 \\ 0 \\ 1 \end{pmatrix}.$$

2. The actuator output is defined as $v = x_1$, where the actuator equations are

$$\dot{x}_1 = 1 + \cos t - x_2,$$

$$\dot{x}_2 = a(x_1, x_2, x_3, t) - (3 + 2 \cos x_3) u_d,$$

$$\dot{x}_3 = \sin(x_1 - x_2 + x_3 - 5t) - x_3 + 0.5 u_d.$$

3. The “unmodeled” (singular) dynamics (actually a part of the actuator) is for the simulation presented by the equation

$$\ddot{u}_d = -2\varepsilon^{-1}\ddot{u}_d - 3\varepsilon^{-2}\dot{u}_d - 2\varepsilon^{-3}(u_d - u).$$

4. $a(x, t)$ represents the system uncertainty. **For a single student (I) and for a pair of students (II):** for both $a = \cos(3 + x_3)$ and $a = \cos(x_2 - 2x_3)$ the same controller is to provide for the exact actuator tracking of the two command signals

$$v_c(t) = 2 \sin(2t + 1) - 1.5 \cos(1.3t), \quad (1)$$

$$v_c(t) = 3 \cos(2t) - \cos(1.2t - 1) + 0.01 \cos 10t.$$

בהצלחה!